

# **ROLAND LX-6**

PREMIUM UPRIGHT DIGITAL PIANO

#### **SOUND GENERATOR**

Piano Sound

Piano Reality Modeling

Max. Polyphony

Piano: Limitless (solo playing using 'Piano' category tones)

Other: 256

#### Tones

Total 324 Tones Grand: 4 Tones Upright: 5 Tones Classical: 5 Tones E.Piano: 12 Tones Organ: 12 Tones Other: 286 Tones

#### **AMBIENCE**

Piano Reality Ambience

Type: Studio, Lounge, Concert Hall, Cathedral

Depth: 11 steps

# **KEYBOARD**

# Keyboard

Hybrid Grand Keyboard (88keys Hammer Action Keyboard): with Escapement, Ebony/Ivory Feel and High Precision Sensing



### **PEDAL**

## Pedal

Damper (Progressive Damper Action Pedal, capable of continuous detection, Damper Modeling)
Soft (capable of continuous detection, function assignable)
Sostenuto (function assignable, with muffler pedal function)

#### **SOUND SYSTEM**

Sound System

Piano Reality Projection

**Speakers** 

Cabinet Speaker: 25 cm (9-7/8 inches) x 1 (with Speaker Box)

Near-field Speakers: (12 cm (4-3/4 inches) x 8 cm (3-3/16

inches)) x 2 (with Speaker Box)

Spatial Speakers: 2.5 cm (1 inches) x 2 (Dome type)

# Rated Power Output

32Wx1

21Wx2

21Wx2

## **HEADPHONES**

Headphones

Piano Reality Headphones Ambience

#### **CABINET**

#### Cabinet

Music rest: with Music holders

Key cover: Slide type, with Keyboard Lid Switch



KLAVIERHAUS

# **TUNING, VOICING**

**Touch Sensitivity** 

Key Touch: 100 steps, fixed touch Hammer Response: Off, 10 steps

**Master Tuning** 

415.3--466.2 Hz (adjustable in increments of 0.1 Hz)

**Temperament** 

10 types (Equal, Just Major, Just Minor, Pythagorean, Kirnberger I, Kirnberger II, Kirnberger III, Meantone, Werckmeister, Arabic), selectable temperament key

**Effects** 

Brilliance

# Piano Designer

Lid

Key Off Noise

Hammer Noise

**Duplex Scale** 

Full Scale String Resonance

Damper Resonance

Key Off Resonance

Cabinet Resonance

Soundboard Type

**Damper Modeling** 

Single Note Tuning

Single Note Volume

Single Note Character

## **INTERNAL SONGS**

Internal Songs

Total 394 songs

Listening: 27 songs



KLAVIERHAUS

Ensemble: 30 songs Entertainment: 20 songs Do Re Mi Lesson: 30 songs

Lesson: 287 songs (Scale, Hanon, Beyer, Burgmuller, Czerny

100)

#### DATA PLAYBACK

## Playable Software

Standard MIDI Files (Format 0, 1)

Audio File (WAV: 44.1 kHz, 16-bit linear format, MP3: 44.1

kHz, 64 kbps--320 kbps, requires USB flash drive)

## **RECORDER**

#### Recordable Software

Standard MIDI Files (Format 0, 3 parts, Approx. 70,000 notes memory)

Audio File (WAV: 44.1 kHz, 16-bit linear format, requires USB flash drive)

#### **BLUETOOTH**

#### Bluetooth

Bluetooth Ver 5.0

Profile: A2DP (Audio), GATT (MIDI over Bluetooth Low

Energy)

CODEC: SBC (Supports SCMS-T content protection)

# **COMPATIBLE ANDROID / IOS APPS (ROLAND)**

Compatible Android / iOS Apps (Roland)

Roland Piano App

## **CONVENIENT FUNCTIONS**



KLAVIERHAUS

#### **Convenient Functions**

Metronome (adjustable

Tempo/Beat/Downbeat/Pattern/Volume/Tone, with Rhythm

Pattern: 80 patterns)

Dual Split

Twin Piano (with Individual Mode)

Transpose (in semitones)

Speaker volume and Headphones volume automatically select

function

Speaker Auto Mute

Volume limit function

Panel Lock

Panel Off

Auto Off

#### **OTHER**

## Display

Graphic LCD 128 x 64 dots

#### Connectors

DC In jack

Input jacks: Stereo miniature phone type

Output (L/Mono, R) jacks: 1/4-inch phone type

USB Computer port: USB B (compatible with USB MIDI/Audio)

USB Memory port: USB A

Phones jack x 2: Stereo miniature phone type, Stereo 1/4-inch

phone type

# **Power Supply**

AC adaptor

# **Power Consumption**

Power Consumption: 28 W (when using the included AC adaptor)

\* Approximate power consumption when playing the piano at the center value of the volume: 19 W

# PIANOART

KLAVIERHAUS

- \* Power consumption when sound has not been played after power-on: 18 W
- \* Power consumption when in OFF mode (when the power automatically turns off): 0.2 W

#### Accessories

Owner's Manual

"Roland Piano Masterpieces"

Leaflet "USING THE UNIT SAFELY"

AC adaptor

Power cord

Headphone hook

## **SIZE AND WEIGHT**

#### Width

1,383 mm

54-1/2 inches

## Depth

493 mm

19-7/16 inches

# Height

1,118 mm

44-1/16 inches

# Weight

LX-6-PE:88.5 kg/196 lbs

LX-6-CH, LX-6-DR:87.0 kg/192 lbs

